



Wiring Assembly Instructions

562024 - Contact, Micro-Power, Solder.



Fig. A. (Contact Sub-Assembly)

Contact Crimp Information Table							
Wire Type	Wire Awg.	Strip Length In Inches	Crimp Tool	Hex Die Set/ Positioner	Indicator	Selector No.	Heat-shrink Length X Dia.
Stranded	18	A) 1/4"	N/A	N/A	N/A	N/A	N/A
	16	B) 1/4					
	14	C) 1/4					

Pull Test Values	
18 Awg	32lbs
16 Awg	39lbs
14 Awg	48lbs



(Values based on M22759/11xx)

(Example of Equipment)

NOTE 1: Refer to **IPC/WHMA-A-620B (Class B)** standard (Ch. 11.1) for cable lengths, measurements and tolerance.

NOTE 2: Overall length of cable should be less 3/8" to compensate for the contact attachment.

STEP 1) Strip wire to dimensions in "Contact Crimp Information" Table using a ruler along with a wire stripper as shown in **Fig. B.**



Fig. B.

ECN#3050	Removed Heat-Shrink and updated to IPC/WHMA-A-620B (Class B)	3/11/2014
----------	--	-----------

STEP 2) Tin stripped wire. (This prevents wire strands from fraying) as in **Fig. C.**



Fig. C.

STEP 3) Put contact in a fixture, insert wire in contact and solder per **IPC/WHMA-A-620B (Class B)** standard (Ch. 4.8.6) for Solder Connections – Cup Terminals.

NOTE: Inspect after insertion of wire into contact to make sure no strands of wire are protruding outside the Cup of the contact.

STEP 4) Remove and inspect Contact and make sure there is no spillage of solder on the outside and meets all standards set in **IPC/WHMA-A-620B (Class B)** standards. **Fig. D.**



Fig. D.